



Signal Consulting, LLC


www.signallc.com

16 Wilelinor Drive, Edgewater, MD 21037-1003 USA

Phone: 410-224-8429, Fax: 410-510-1821, E-mail: info@signallc.com

Si24SB4-VD2-30V-20A-AP1, Smart H-Bridge, with Variable or Fixed Ramp Delay Time for Soft-Start and Soft-Stop, Integrated Aluminum Plate Heat-Sink, 5kHz or 20kHz PWM, Active Low Control Inputs, Y-Chip


The **Si24SB4-VD2-30V-20A-AP1** is a 30V 20A, microprocessor based, high-power, Smart H-Bridge with a small (4.0"x3.3"x0.062") Aluminum Plate Heat Sink and with user selectable Soft-Start and Soft-Stop features. This controller uses a single (9V to 30V at 0 to 20A) DC power supply to control the speed of a DC motor (or load-current) in forward or reverse direction. An onboard microprocessor generates a 5kHz or 20kHz **PWM** carrier signal, controls the load-power (or motor speed), controls the load-current rate (or motor acceleration and deceleration). The **PWM** carrier frequency is user selectable by the jumper **J2**, 20kHz when **J2** is open and 5kHz when short. This high frequency PWM rate insures a quiet motor environment. The user can choose between variable delay-mode (variable motor acceleration/deceleration) or can choose a fixed delay-mode. In the variable mode (with jumper **J1** installed), the rise-time/fall-time varies linearly with the analog voltage on pin **I2** ($V_{I2,G}$ on **CN6**) (from 0.1sec=0V to 2.0 sec=+5V). In the fixed mode (with jumper **J1** open) the rise-time/fall-time is fixed to approximately 2sec. As the name "Smart" implies the required motor speed (or PWM pulse-duration) is variable from 0 to 100% in 0.83% steps using the analog voltage ($V_{I1,G}$ on **CN6**), while the motor direction (or Load-Current Direction) is selected using two active low digital (0 to +5V) control signals ($V_{F,N}$ and $V_{R,N}$) or switches. All inputs are optically isolated or zener-diode protected. A bicolor LED is used to monitor the motor (or load) voltage (Red = Forward, Green = Reverse). A small (4.0"x3.3"x0.065") integrated Aluminum Plate Hear-Sink is used to operate at 20A current levels. Higher current-levels (25A or 750W) can be achieved with more efficient heat-sinks. Please click on this link and read the [Board Mounting Instructions and Heat Sink Selection Guide](#). This board operates in a wide voltage-range (9V to 50V) at max. continuous load current of 20A. Typical applications are: Bi-directional DC Motor-Speed Controller, Peltier Effect TE Coolers, Heat Pumps, DPDT Solid State Relay, etc. This board can be configured and programmed to perform efficiently in many customized applications.



Motor Control-Action Truth Table, (Pins on Connector CN4)

$(V_{F,N})$ Voltage at Pin F relative to pin N	$(V_{R,N})$ Voltage at Pin R relative to pin N	Operation Mode of Motor or Load
$V_{F,N} = 5V$ or pin Open	$V_{R,N} = 5V$ or pin Open	Stop Rotatio (Motor Open)
$V_{F,N} = 0V$ @ 2mA Sink	$V_{R,N} = 5V$ or pin Open	Forward Rotation with V_{PWM} Control
$V_{F,N} = 5V$ or pin Open	$V_{R,N} = 0V$ @ 2mA Sink	Reverse Rotation with V_{PWM} Control
$V_{F,N} = 0V$ @ 2mA Sink	$V_{R,N} = 0V$ @ 2mA Sink	Stop Rotation (Motor Open)

The motor action or load-current direction is controlled by active low control inputs, (0 to +5V) applied to Pin **F** (Forward) and/or pin **R** (Reverse) relative to Pin **N** (Neutral) on the Connector **CN4**. These pins are optically isolated from the H-Bridge, providing good noise immunity for these inputs. The control actions and the required voltage levels are defined by the Truth-Table listed above. All control lines (analog and digital) are sampled approximately at 80Hz rate in the fast mode (**J1** jumper open), and at 8Hz rate in the slow mode (**J1** jumper short).



Signal Consulting, LLC

16 Wilelinor Drive, Edgewater, MD 21037-1003 USA

Phone: 410-224-8429, Fax: 410-510-1821, E-mail: info@signallc.com

Specification and Application of **Si24SB4-VD2-30V-20A-AP1**

- **Typical Operating Temperature at 20A:** 45°C with the Metal Heat-Ring Bolted to the (4.0"x3.3"x0.065") Aluminum Plate Heat-Sink, while it is exposed to air at 25°C (as shown on photograph).
- **Source-Voltage Requirements:** V_P (from pin +P to pin -P) 9V to 30V, unregulated DC voltages.
- **Average Load Voltage (from pin +L to pin -L):** 0V at 0% Duty-Cycle and V_P at 100% Duty-Cycle.
- **Max. Continuous Load Current:** 20A at 100% Duty-Cycle.
- **Max. Load Current for 5Sec:** 40A at 100% Duty-Cycle.
- **Two User Selectable Motor Acceleration/Deceleration Modes:** Using Jumpers J1.
- **Load Isolation:** The Load or Motor must be isolated from the source voltage (V_P).
- **Power-Conversion Efficiency:** Approximately 98.5% at full-load (30V and 20A).
- **Load-Current Indicator:** An onboard bicolor LED is used to monitor the motor (or load) voltage (Red = Forward, Green = Reverse).
- **Voltage Requirement:** The Si24 will work with any DC Load in the 9 V to 30 V range. In addition, the power filters are included on this board. Consequently, only unregulated (full-wave rectified) DC input power is required in most applications.

A Typical Application of the **Si24SB4-VD2-30V-20A-AP1**

In this open-loop application, the PWM (or motor speed) and the ramp up/down time (motor acceleration/deceleration) in forward or reverse direction are independently adjusted with two external linear 1-turn 5kΩ potentiometers (Signal Part number [Si5Pot1-5k](#)) and the motor direction is controlled by 4 external switches (Signal Part number [Si24PB2-MC3](#)) connected to port **CN4** (as shown below). The normally-open switches select the motor direction, while the optional normally-closed limit-switches are included to prevent over-rotation in window-lifting applications. **Warning: The connecting wires to the Load and the Power Supply must be heavy gauge copper wire (#12 AWG or heavier) to handle the rated current level. In addition, these heavy gauge wires act as a heat sink, protecting the board from overheating.**

